



DIESELDRIVEN POWER GENERATOR

Dimensions

Length(mm).....: 910 Width(mm).....: 520 Height(mm).....: 680
 Weight (kg).....: 100
 Lifting/ Transportation.....: Transportation on pallet

Construction year

Built.....: 2009

Area of use / certification

Onshore/offshore.....: Onshore

Type

Fabricator.....: Power Mate
 Model.....: SMT 6000

Flow / Pressure / Volume

Diesel Tank Volume (ltr).....: 16

Connections

Outlet connection.....: 1 ea Industry 5 pins 6h + j
 AC Voltage Output.....: 1-Phase 230V/7,5A
 3-Phase 400V/32A
 AC Output max (kW).....: 5 kW (50Hz) 6 kW (60 Hz)
 AC Output rated (kW).....: 4,6 kW (50 Hz), 5,2 kW (60 Hz)
 DC Output.....: 12 V / 8,3 A

Pump(s)

Aggregate.....: Diesel Generator SMT 6000
 Brushless, Self-exciting, 1-fase and 3-fase

Motor / Engine(s)

Motor1 (type).....: Foreed air cooled, 4-stroke, Diesel engine 10hp/3600 rpm

Power supply

Starter.....: Recoil + Electric starter

Additional information

Equipment / Functions.....: - 69 dB@50Hz, 70 dB@60Hz measured at 7metres
 - Can run continuous in 9,5 hours @ 50 Hz on one tank
 - Can run continuous in 8,5 hours @ 60 Hz on one tank